## LEONARDO ELECTRONICS

# SUPERHAWK C LOW SWAP, MEDIUM WAVE INFRARED DETECTOR

The Low Size, Weight and Power (SWaP) SuperHawk C infrared detector is a compact 1280 x 1024 Mercury Cadmium Telluride (MCT) Integrated Detector Cooler Assembly with 8um pitch pixels. The EO performance from the Standard SuperHawk detector is retained, retaining key features such as a near perfect modulation transfer function (MTF), resulting in the sharpest images typically characterised by the company's unique technology.

The Low SWaP SuperHawk C variant utilises the European common cold finger standard, enabling SuperHawk C to operate with the next generation of microcoolers. The shorter cold finger associated with this design allows for a significantly more compact IDCA. Comparing a Standard SuperHawk fitted with a Thales RM2, to a Low SWaP SuperHawk with a Thales RMs1 leads to a 42% mass reduction, a 20% length reduction in the optical axis and up to a 30% reduction in cooler power consumption and cooldown time.

## MAIN FEATURES

- Medium waveband (3.7-5µm)
- 1280 x 1024 format
- 8µm x 8µm pixels
- SXGA format
- Selectable 720-HD format
- · Size and Weight reduction from Standard SuperHawk
- Easy SXGA upgrade from 16µm sensors
- Easy HD upgrade from 15µm SD formats
- Negligible pixel blur
- >110K Operation

## **KEY BENEFITS**

- · Even more Compact than SuperHawk
- Low power
- High resolution
- · Easy interface with digital proximity electronic



# TECHNICAL SPECIFICATION FORMAT

Array size Mode 1	1280 x 1024 pixels
Mode 2	1280 x 720 pixels
Pixel pitch	8μm
Active area Mode 1	10.24 x 8.19mm
Mode 2	10.24 x 5.76mm
Image diagonal Mode 1	13.1mm
Mode 2	11.75mm

### ELECTRO-OPTIC

3.7µm to 4.95µm
f/2.8, f/3.2, f/3.4 f/4
19mm above FPA
27mK (typical with supplied electronics)
>99.5% (typical)
110K
ITR or IWR
Programmable
4.1Me-/2.6Me-selectable
±0.5%
8
>80Mpix/sec

#### **PROXIMITY ELECTRONICS**

Supply voltage	5V
Power	<3W
Interface	Digital
ADC resolution	14 bits
Video output	Serial LVDS

## **IDCA**

Cooler	Thales RMs1
	(Other cooler options are available)
Weight	200g
	(with RMs1 and no proximity electronics/CCM)
Cooldown time	<4 minutes
Power consumption	from 2.2W Steady State
Operating temperature	-40°C to +70°C



Low SWaP SuperHawk C with Thales RMs1



#### For more information:

infomarketing@leonardo.com

Leonardo Electronics

First Avenue - Millbrook Industrial Estate - Southampton - Hampshire - SO15 0LG - United Kingdom - T + 44 (0) 2380 702300

This publication is issued to provide outline information only and is supplied without liability for errors or omissions.

No part of it may be reproduced or used unless authorised in writing. We reserve the right to modify or revise all or part of this document without notice.

2023 © Leonardo UK Ltd

LDO\_UK23\_00122 04-23

